# **BIKESPEED-KEY**

#### Panasonic with plugable Cable set

for Panasonic X1-motors from 2017 to 2019

## **Product description**



bikespeed-key is a simple and compact kit consisting of a tuning-chip and a cable set to bypass the speed limit of 25km/h in Panasonic Pedelec engines.

The chip bisects the speedometer from a velocity of about 7km/h. This way, the scope of the support provided by the engine is enhanced to a maximum of 50km/h.

After installing <sup>1</sup>) the cable set, which can simply be put between engine and speed sensor, the chip can be plugged in and out at any time (even while riding).

### **Product Liability / Liability Exclusion**

We were not able to figure out whether running the bikespeed-key with the cable installed but without a chip plugged in is permitted on public roads. That is why we expressly point out that the mere installation of the interface may already be an offence against (german) road traffic regulations, driving without insurance, §6 obligatory-insurance law respectively! We therefore recommend using a modified bicycle on private property only. Running the bikespeed-key in public traffic is expressly prohibited by road traffic regulations!

Installing and running the bikespeed-key is done in personal responsibility; liabilities for damages or subsequent damages as well as legal consequences for bikespeed are excluded in every case.

Please inquire about legal consequences that may result for you from installing the system before you use it.

date: 11.12.2019 page 1

We expressly point out that using the bikespeed-key leads to a loss of warranty by the manufacturer. Furthermore there are no claims to product liability for your pedelec/e-bike viable for the manufacturer and bikespeed.

bikespeed especially cannot guarantee that brakes, frames, running gears, tires etc. are designed for the use of the tuning-component.

Attention: Only plug the bikespeed-key into the connection cable provided. Never plug it into a USB-slot (e.g. on your PC)!

## **Installation:**

**<u>Attention:</u>** - Remove the battery before working on your bicycle!

- the installation may only be conducted by an expert!

- All information without guarantee!

For the installation of the bikespeed-key with plugable cable set two of the three screws holding the engine have to be removed; the engine can easily be folded down and all of the connectors become accessible.

### Installing the bikespeed-key cable set:

Tools required: allen key set

 Loosen and remove the two screws shown on the right side (chain side) with an Allen key size 6



2. On the left, loosen the screw (1) shown on the left with a 6-inch Allen key. The screw remains in place and serves as a hinge for the engine to be folded down (2).



3. Locate the 2-pin connector from the speed sensor (white, rectangular, 2-pole). These are probably hidden in the frame. Just follow the cables.



 Connect the pins just loosened with the pins of the bikespeed cable set.



 Attach the socket of the bikespeed cable set to the desired spot on your bicycle. Use e.g. cable ties in order to attach the socket and the cable.



6. Lead the cable to the area of the connectors

When placing the cable mind that it does not end up in the area of movable parts and attach it to the bicycle, e.g. with cable ties. The cable of the bikespeed-key cable set can be shortened to the length required.

 Skin the brown and grey conductor of the bikespeed- cable set (USBslot) by about 5mm.


We recommend <u>not</u> to tin-coat the ends!

 Connect the skinned conductors to the screw terminals. Use a slotted screwdriver with a 2.5mm blade to screw the cables in, or use the screwdriver included.





Please use the following classification for the connection of the cables:



The screw terminal for the green conductor of the bikespeed-cable set is additionally marked with a red point.

- 9. Put the connectors into the hollow between engine and frame and lift the engine in order to first fasten the Allen screws provisionally and then fasten all three screws tightly (Please note the torque: keep to the specifications of the producer).
- 10. Reattach all the covers removed before.
- 11. Reinsert the battery.

Put the bikespeed-key into the socket of the cable set and off we go!



Have fun, your bikespeed-team!

#### All statements without guarantee!

1) We point out that the installation may only be carried out by an expert.

## **Hint for disposal**

Electric and electronic devices that have become waste are called old devices. Owners of such old devices have to bring these to recycling facilities, where these are handled and recorded separately from urban solid waste. Old devices must not end up in the household refuse. In fact they have to be collected in special collecting and recycling systems.

Owners of old devices from private households can dispose these at the public waste disposal authorities or bring them to producer or seller related disposal locations. You can find these disposal locations online:

https://www.ear-system.de/ear-verzeichnis/sammel-und-ruecknahmestellen.jsf

The labelled symbol showing the "crossed out waste container" on electric and electronic equipment indicates that the concerning equipment has to be disposed separately from urban solid waste.



As a producer in terms of the German ElektroG we are registered with the German registration authority Stiftung Elektro-Altgeräte-Register (Benno-Strauß-Str. 1, 90763 Fürth), having been granted the following WEEE registration

number: DE 87104747

As well at the Elektro Recycling Austria (ERA) GmbH with contract

number: 40624

## **EC Declaration of Conformity**

The manufacturer bikespeed GmbH

Huberstr. 17

97084 Wuerzburg

Hereby declares that the following product:

Product name: bikespeed-key kit

Production year: 2013-2020

is in accordance with all appropriate regulations of the EMV-guideline (EMC) 2004/108/EU, the disposal-guideline 2012/19/EU as well as the RoHS-guideline 2011/65/EU.

Name of the documentation agent: Matthias Braun

Adress of the documentation agent: see adress of the manufacturer

Wuerzburg,

11.12.2019 Matthias Braun, CEO

Date Signee Signature



